

## DigiOx Finger Pulse Oximeter

The DigiOx Finger Pulse Oximeter provides simple, fast, and accurate oxygen saturation (SpO2) and pulse rate measurements. Its lightweight and compact design makes it an ideal solution for home, clinical and EMS settings.

### Features & Performance:

- Lightweight, pocket-size solution
- Provides fast and accurate SpO2 and pulse rate measurements
- Multiple-directional display for easy read
- Large LED color display that is easy to read
- Adjustable 10 settings for brightness level
- Simple one button operation
- Automatic power off function to conserve batteries
- Accommodates widest range of finger sizes from pediatric to adult

### Display:

Oxygen saturation (SpO2), Pulse rate and Plethysmogram  
Multi-directional display so readings can be viewed from any angle

### Display Range:

SpO2: 70% to 99%  
Pulse Rate: 30 to 235 bpm

### Accuracy (% SpO2):

70% - 100% ±3%

### Pulse Rate Accuracy:

30-99bpm, ±2bpm  
100-235bpm, ±2%

### Alarms:

Low Battery indicator

**JB02008**            1 ea



### Technical Specifications

Power Supply Requirement.....Two (2) 1.5V AAA alkaline batteries  
Operating Temperature Range..... 41 F – 104F (5C – 40C)  
Operating Relative humidity..... 15% to 80% RH  
Operating Atmospheric pressure.....10.15 psi to 15.37 psi (70kPa to 106kPa)  
Storage Temperature Range..... -4°F to 131°F (-20°C - 55°C)  
Storage Relative humidity..... < 85%  
Size..... 2.28" x 1.26" x 1.34" (58mm x 32mm x 34mm)  
Weight..... 2 oz (50g) (including batteries)